

IPSO WE COIN OP

THE PROFESSIONALS CHOICE





SPECIFICATIONS

Details	Units	16	22	30	35	40
Capacity	Kg (lb)	7.5 (16)	10 (22)	13.5 (30)	16 (35)	18 (40)
Height	mm	1005	1100	1170	1170	1170
Width	mm	660	660	780	780	780
Depth	mm	730	830	785	885	885
Net Weight	Kg	170	178	235	245	308
Drum Volume	m3	0.073	0.095	0.132	0.165	0.181
G.Force	G's	74	74	88	88	71
Door Opening Dia	mm	300	300	300	300	395
Control		MICRO 20	MICRO 20	MICRO 20	MICRO 20	MICRO 20
Fixing Down		Bolt	Bolt	Bolt	Bolt	Bolt
Electrics- Boiler Fed (Special Order)	Volt/ph/amp	240/1/16	240/1/16	240/1/16	n/a	n/a
Electrics- Boiler Fed	Volt/ph/amp	415/3/10	415/3/10	415/3/10	415/3/10	415/3/10
No.of Water Connections	cold/hot	2/1	2/1	2/1	2/1	2/1
Size	"BSP	3/4	3/4	3/4	3/4	3/4
Drain Connection (Gravity)	mm	50	50	50	50	50



IPSO WE COIN OP

WE16, 22, 30, 35 & 40 Rigid Mount, Micro 20

The WE range of washing machines has been specially designed for the launderette of today. The robust build of WE washers is perfectly complemented by the latest technological and mechanical features such as the Micro 20 microprocessor system and the JLA Coin Mech. And for good practice and complete peace of mind, all models are fitted with a built in Type 'A' Air Gap.

The Ipso brand is an emblem of quality throughout the industry. Its coin-operated washers are reputed for excellence, and are used by over 70% of UK launderettes.

Features	Benefits to customer
Built in Type 'A' Air Gap	Fully approved for direct connection to mains water, resulting in lower installation costs and more space - no storage tank required
Micro 20 controlled	Easy to use, reducing the likelihood of user error and keeping maintenance simple. Standard with 6 customised wash cycles to suit induviduals needs
Boiler fed	Fast, economical cycles. More loads per day means more income
JLA Coin Mech	Any coin any currency, the only mech you'll ever need
High build quality with stainless steel cabinet and drums	Robust and reliable. Secured to metal or concrete plinth to remove all vibration and ensure long life
Digital display	Shows value needed to start machine and counts down as coins are added Displays cycle selected and minutes remaining until end of cycle.